

Model Configurations/kA Ratings

E100 Manual Transfer Switch

Amperage	Poles	Voltage	Standard/Fused WCR
100A 150A 200A 225A 400A	2, 3, 4	A = 600V B = 208V C = 240V D = 416V E = 480V	Standard (un-fused): 100A-200A – 10kA 225A-400A – 14kA 600A-1200A – 35kA
600A 800A 1000A 1200A	3, 4		Fused: Not Available

E200 ATS, Non-Bypass

Amperage	Poles	Voltage	Standard/Fused WCR
100A 150A 200A	2, 3, 4	A = 600V B = 208V C = 240V D = 416V E = 480V	Standard: 100A-200A – 10kA Fused: 100kA
225A 400A	2, 3, 4		Standard: 14kA Fused: 65kA
600A 800A 1000A 1200A	3, 4		Standard: 35kA Fused: Not Available

E301 ATS, Single-Sided Bypass/Isolation

Amperage	Poles	Voltage	Standard/Fused WCR
100A 150A 200A	4	A = 600V B = 208V C = 240V D = 416V E = 480V	Standard: 10kA Fused: 100kA
225A 400A	2, 3, 4		Standard: 14kA Fused: 65kA
600A	3, 4		Standard: 35kA Fused: 100kA
800A	3, 4		
1000A 1200A	3		Standard: 35kA Fused: Not Available

E302 ATS, Single-Sided Bypass/Isolation

Amperage	Poles	Voltage	Standard/Fused WCR
100A 150A 200A	2, 3, 4	B = 208V C = 240V D = 416V E = 480V	Standard: 10kA Fused: 100kA
225A 400A	2, 3, 4		Standard: 14kA Fused: 65kA
600A	3, 4		Standard: 35kA Fused: 100kA
800A	3, 4		
1000A 1200A	3		Standard: 35kA Fused: Not Available

E313 ATS, Single-Sided Bypass/Isolation

Amperage	Poles	Voltage	Standard/Fused WCR
100A 150A 200A	2, 3	A = 600V B = 208V C = 240V D = 416V E = 480V	Standard: 10kA Fused: 100kA

E601 ATS, Double-Sided Bypass/Isolation

Amperage	Poles	Voltage	Standard WCR
100A 150A 200A	2, 3, 4	A = 600V B = 208V C = 240V D = 416V E = 480V	Fused: 100kA
225A 400A	2, 3, 4		Fused: 65kA
600A	3, 4		Fused: 100kA

E602 ATS, Double-Sided Bypass/Isolation

Amperage	Poles	Voltage	Standard WCR
100A 150A 200A	2, 3, 4	B = 208V C = 240V D = 416V E = 480V	Fused: 100kA
225A 400A	2, 3, 4		Fused: 65kA
600A	3, 4		Fused: 100kA

Models are comprised of the series, amperage, # of poles, voltage and whether it is fused or not. The convention is: **Series + Amperage + Poles + Voltage + “-F”** (Fused on both sources) or **“-F1”** (Fused on S1/Normal)

- Example #1: E301-225A-3A-F (Single Sided Bypass, 225A, 3 Poles, 600A, Fused on S1 and S2)
- Example #2: E301-225A-3A-F1 (Single Sided Bypass, 225A, 3 Poles, 600A, Fused on S1/Normal only)
- Example #3: E301-225A-3B (Single Sided Bypass, 225A, 3 Poles, 208V, Non-Fused)
- Example #4: E200-400A-4A (Non Bypass, 400A, 4 Poles, 600A, Non-Fused)